

- ◆ Built-in radio, receiver, radio control
- ◆ Record or erase transmitter at anytime
- ◆ Programming by transmitter



Power: 230V/50HZ

Model	Torque Nm	Rev r.p.m	Power w	Current A	Diameter mm	Grade of protection	Runningtime Min	L mm
EY35-3/28	3	28	90	0.37	35	IP44	4	445
EY35-5/28	5	28	100	0.44	35	IP44	4	445
EY35-6/14	6	14	90	0.37	35	IP44	4	445
EY35-8/14	8	14	100	0.44	35	IP44	4	445

Power: 120V/60HZ

Model	Torque Nm	Rev r.p.m	Power w	Current A	Diameter mm	Grade of protection	Running time Min	L mm
EY35-3/30	3	32	90	0.74	35	IP44	4	445
EY35-5/30	5	32	100	0.88	35	IP44	4	445
EY35-6/16	6	16	90	0.74	35	IP44	4	445
EY35-8/16	8	16	100	0.88	35	IP44	4	445